






























International Cord Set Configurations

This information is in accordance with the EN 60799 standard. Reference IEC 60083 for plug requirements and IEC 60320-1 for connector requirements. Plug configurations listed below are the most commonly used. See IEC 60083 for less commonly used plugs.

IEC 60320 Connectors International Plug Faces			0.2A	2.5A		6A	10A International				16A International		
			Class II	Class I	Class II	Class II	Class I			Class II	Class I		Class II
													
International Plug Faces			C1	C5	C7	C9	C13	C15	C15A	C17	C19	C21	C23
Argentina		10A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	X	X	X
		20A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	X	X	X
Australia		10A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	X	X	X
		10A Ungrounded	✓ ³	X	✓ ³	✓ ³	X	X	X	✓ ³	X	X	X
		15A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	X	X	X
Brazil		10A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	X	X	X
		20A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
China		10A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	X	X	X
		16A	X	X	X	X	X	X	X	X	✓ ¹	✓ ¹	X
Continental Europe		16A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
Denmark		16A Max	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
Europlug		2.5A	✓ ³	X	✓ ³	X	X	X	X	X	X	X	X
France/Belgium		16A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
India		6A	X	✓	X	X	X	X	X	X	X	X	X
		16A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
Israel		16A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
Italy		10A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	X	X	X
		16A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
Japan		15A Grounded	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	X	X	X
		15A Ungrounded	✓ ³	X	✓ ³	✓ ³	X	X	X	✓ ¹	X	X	X
Korea		16A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
Russia		16A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
Saudi Arabia		3A	✓	✓	✓	X	X	X	X	X	X	X	X
		5A	✓	✓	✓	X	X	X	X	X	X	X	X
		10A	X	✓	X	✓	✓ ¹	✓ ¹	✓ ¹	✓ ¹	X	X	X
		13A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	✓ ¹	X	X	X
South Africa		6A	X	✓	X	X	X	X	X	X	X	X	X
		16A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
		16A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
Switzerland		10A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	X	X	X
		16A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	X	✓ ²	✓ ²	X
United Kingdom/ Ireland <small>Note: The BS 1363 plug can either be a Class I or a Class II plug</small>		3A	✓	✓	✓	X	X	X	X	X	X	X	X
		5A	✓	✓	✓	X	X	X	X	X	X	X	X
		10A	X	✓	X	✓	✓ ¹	✓ ¹	✓ ¹	✓ ¹	X	X	X
		13A	X	✓	X	X	✓ ¹	✓ ¹	✓ ¹	✓ ¹	X	X	X

- ✓ Compliant per IEC 60799
- ✓ Compliant per SABS 1661
- X Not compliant per IEC 60799/SABS 1661

- 1—Cord set may not exceed 2 meters on .75mm² cable. Reference IEC 60320-1
- 2—Cord set may not exceed 2 meters on 1.0mm² cable. Reference IEC 60320-1
- 3—Cord set may not exceed 2 meters on .5mm² cable. Reference IEC 60320-1

A cord set is defined as an assembly consisting of one flexible cable or cord fitted with one plug and one connector.

NOTE: For cable type, size, and material refer to end use product application.